

RIP LINE

4280 (4x90 Watts rms)



KEY POINTS

- Four-channel power amplifier (4 x 90Wrms into 2 ohms)
- Bridged mode (2 x 160Wrms into 4 ohms)
- AB class amplifier
- High and low-level inputs
- Very low distortion 0.2% @ 1kHz
- Bass Boost: 0 +6dB +12dB
- Choice of filtering: Full, High-pass, Low-pass (12dB/octave)

SPECIFICATIONS

Maximal power measured at 13.8V continuously into 4 ohms	4x140W
Maximal power measured at 13.8V continuously into 2 ohms	4x180W
Nominal power measured at 13.8V continuously into 4 ohms	4x70Wrms
Nominal power measured at 13.8V continuously into 2 ohms	4x90Wrms
Maximal power in bridged mode measured at 13.8V continuously into 4 ohms	2x320W
Nominal power in bridged mode measured at 13.8V continuously into 4 ohms	2x160Wrms
Signal/noise ratio	95dB
Frequency response (-1dB)	6Hz – 60kHz
Variable high-pass crossover	50 – 300Hz
Variable low-pass crossover	50 – 300Hz
Adjustable Bass-Boost level	0, +6, +12dB
Total Harmonic Distortion (THD)	0.2%
Protections	Short-circuit Thermal overload Polarity error
	Fuse
Dimensions (HxWxD)	55x220x360mm 2 ^{3/16} x 8 ^{2/3} x 14 ^{3/16} "

MECHANICAL DRAWING

